KOHLER

Industrial Diesel Generator Set – J130



 RATINGS 400 V - 50 Hz

 Standby
 kVA
 130

 kWe
 104

 Prime
 kVA
 118

 kWe
 94



GENERAL SPECIFICATIONS

Engine brand	JOHN DEERE
Alternator commercial brand	KOHLER
Voltage (V)	400/230
Standard Control Panel	APM303
Optional control panel	APM403
Optional Control Panel	M80
Optional control panel	Terminal block
Consumption @ 100% load ESP (L/h) *	29
Consumption @ 100% load PRP (L/h) *	27
Emission level	Fuel consumption optimization
Type of Cooling	Radiator
Performance class	G3

GENERATOR SETS RATINGS

				Standby Rating Prime Rat			Rating	
	Voltage	PH	Hz	kWe	kVA	Amps	kWe	kVA
	415/240	3	50	104	130	181	94	118
	400/230	3	50	104	130	188	94	118
J130	380/220	3	50	104 130 198 94 118				118
	240 TRI	3	50	104	130	313	94	118
	230 TRI	3	50	104	130	326	94	118
	220 TRI	3	50	104	130	341	94	118
DIMENSIONS	5 СОМРАСТ	VERS	ION					
Length (mm)						1950		
Width (mm)						1084		
Height (mm)						1455		
Tank capacity	y (L)					190		
Dry weight (k	Dry weight (kg) 1083							
DIMENSIONS	SOUNDPR	DOFEI	D VERS	SION				_
Type soundp	roofing				NO	T AVAILA	BLE	_
Length (mm)						2572		
Width (mm)						1126		
Height (mm)						1571		
Tank capacity	y (L)					190		
Dry weight (k	(g)					1405		
Acoustic pres (75% PRP)	ssure level @)1m ii	n dB(A)) 50Hz		79		
Acoustic pres (75% PRP)	ssure level @	07m ii	n dB(A)) 50Hz		67		
* Volumetric	Fuel consun	nntior	n is un	to 4% his	oher w	hen usin	σ HVO I	than

* Volumetric Fuel consumption is up to 4% higher when using HVO than Diesel Fuel

Reference Conditions: 25°C Air Inlet Temperature, 40°C Fuel Inlet Temperature, 100 kPa Barometric Pressure; 10.7 g/kg of dry air Humidity. Intake Restriction set to maximum allowable limit; Fuel density at 0.85 kg/L.

Data was taken from a single engine test according to the test methods, fuel specification and reference conditions stated above and is subjected to instrumentation and engine-to-engine variability. Test conducted with alternate test methods, instrumentation, fuel or reference conditions can yield different results. Data and specifications subject to change without notice.

Benefits & features

KOHLER premium quality

- Design offices using the latest technical innovations
- Modern fully certified factories
- A cutting edge laboratory
- The generating set, its components and a wide range of options have been fully developed, prototype tested, factory built, and production tested
- Approved for use with HVO (Hydrotreated Vegetable Oil) according to EN15940

KOHLER premium performances

- Optimized and certified sound levels
- Reliable power, even in extreme conditions
- Optimized fuel consumption
- Compact footprint
- Best quality of electricity, high starting and loading capacity, according to ISO8528-5
- Robust base frames and high-quality enclosures
- Protection of installations and people
- Approved in line with the most stringent standards

Engines

- Premium level engines, in-house or from strong partners
- High power density, small footprint
- Low temperature starting capability
- Long maintenance interval

Alternator

- Provide industry leading motor starting capability
- Made in Europe
- Built with a class H insulation and IP23

Cooling

- A compact and complete solution using a mechanically driven radiator fan
- Designed or optimized by KOHLER
- High temperature and altitude product capacity available
 Base frame and enclosure

base frame and enclosure

- High quality steel with enhanced corrosion resistance
- Highly durable QUALICOAT-certified epoxy paint
- Minimum 1000 hours of resistance to salt spray in accordance with ISO12944
- Ergonomic access to allow easy maintenance and connection of the generator
- Robust design optimized for transportation

KOHLER.

Engine

General	
Engine brand	JOHN DEERE
Engine ref.	4045HSG21 *
Air inlet system	Turbo
Fuel	Diesel Fuel/HVO
Emission level	Fuel consumption optimization
Cylinder configuration	L
Number of cylinders	4
Displacement (I)	4,48
Bore (mm) * Stroke (mm)	106 * 127
Compression ratio	17 : 1
Speed 50Hz (RPM)	1500
Maximum stand-by power at rated RPM (kW)	122
Charge Air coolant	Air/Air
Frequency regulation, steady state (%)	+/- 2.5%
Injection Type	Direct
Governor type	Mechanical
Air cleaner type, models	Dry
Fuel system	
Maximum fuel pump flow (I/h)	69
Max head on fuel return line (m fuel)	1
Consumption with cooling system	
Fuel consumption @ ESP Max Power (I/h)	31,10
Fuel consumption @ PRP Max Power (I/h)	28,10
Fuel consumption @ 75% of PRP Power (I/h)	21,40
Fuel consumption @ 50% of PRP Power (I/h)	15

Emissions

Emission PM 50Hz (g/kW.h)	0,6340
Emission CO 50Hz (g/kW.h)	1,70
Emission NOx 50Hz (g/kW.h)	6,40
Emission HC 50Hz (g/kW.h)	0,10

* Engine reference may be partially modified depending on genset application, options selected by the customer and lead time required.

Lubrication System			
Oil system capacity including filters (I)			
Min. oil pressure (bar)			
Max. oil pressure (bar)			
Oil sump capacity (I)	14	,70	
Oil consumption 100% ESP 50Hz (I/h)	0,0	780	
Air Intake system			
Max. intake restriction (mm H2O)	6	25	
Combustion air flow (l/s)	142		
Exhaust system			
	PRP	ESP	
Exhaust gas flow (L/s)		393	
Exhaust gas temperature @ ESP (°C)	6	10	
Max. exhaust back pressure (mm H2O)	750		
Cooling system			
Radiator & Engine capacity (I)	15	,20	
Fan power 50Hz (kW)	2,	50	
Fan air flow w/o restriction (m3/s)	3,	80	
Available restriction on air flow (mm H2O)	2	20	
Type of coolant	Glycol-I	Ethylene	
Radiated heat to ambiant (kW)	1	.1	
Heat rejection to coolant HT (kW)	2	8	
HT circuit flow rate (I/min)	1	20	
Coolant capacity HT, engine only (I)		9	
Max coolant temperature, Shutdown (°C)	1	05	
Thermostat begin of opening HT (°C)	82		
Thermostat end of opening HT (°C)	g	94	

Reference Conditions: 25°C Air Inlet Temperature, 40°C Fuel Inlet Temperature, 100 kPa Barometric Pressure; 10.7 g/kg of dry air Humidity. Intake Restriction set to maximum allowable limit for clean filter; Exhaust Back pressure set to maximum allowable limit; Fuel density at 0.85 kg/L. Data was taken from a single engine test according to the test methods, fuel specification and reference conditions stated above and is subjected to instrumentation and engine-to-engine variability. Test conducted with alternate test methods, instrumentation, fuel or reference conditions can yield different results. Data and specifications subject to change without notice.

KOHLER.

Industrial Diesel Generator Set – J130

(%)

20%

15% Chite do 10%

Alternator opecifications	
Alternator commercial brand	KOHLER
Kohler Alternator description	KH01051T
Number of pole	4
Number of bearing	Single Bearing
Technology	Brushless
Indication of protection	IP23
Insulation class	Н
Number of wires	06
AVR Regulation	Yes
Coupling	Direct
Capacity for maintaining short circuit at 2.7 In for 5 s	Yes
Application data	
Overspeed (rpm)	2250

Overspeed (rpm)	2250	
Power factor (Cos Phi)	0,80	
Voltage regulation at established rating (+/- %)	0,50	
Wave form : NEMA=TIF	<50	
Wave form : CEI=FHT	<2	
Total Harmonic Distortion in no-load DHT (%)	<3.5	
Total Harmonic Distortion, on linear load DHT (%)	<5	
Recovery time (Delta U = 20% transcient) (ms)	500	
Performance datas		
Continuous Nominal Rating 40°C (kVA)	125	
Unbalanced load acceptance ratio	8	

Peak motor starting (kVA) based on x% voltage dip power factor at 0.3

150 200 250 kVA à Cose 0.3 - Rotor Bloqué / kVA at Cose 0.3 - Locked ro

Alternator Standard Features

- All models are brushless, rotating-field alternators
- NEMA MG1, IEEE, and ANSI standards compliance for temperature rise and motor starting
- The AVR voltage regulator provides superior short circuit capability
- Self-ventilated and dip proof construction
- Superior voltage waveform

Note: See Alternator Data Sheets for alternator application data and ratings, efficiency curves, voltage dip with motor starting curves, and short circuit decrement curves.

Reference Conditions: 25°C Air Inlet Temperature, 40°C Fuel Inlet Temperature, 100 kPa Barometric Pressure; 10.7 g/kg of dry air Humidity. Intake Restriction set to maximum allowable limit for clean filter; Exhaust Back pressure set to maximum allowable limit; Fuel density at 0.85 kg/L. Data was taken from a single engine test according to the test methods, fuel specification and reference conditions stated above and is subjected to instrumentation and engine-to-engine variability. Test conducted with alternate test methods, instrumentation, fuel or reference conditions can yield different results. Data and specifications subject to change without notice.



Dimensions compact version

Length (mm) * Width (mm) * Height (mm)	1950 * 1084 * 1455
Dry weight (kg)	1083
Tank capacity (L)	190

M138 - Dimensions soundproofed version

Length (mm) * Width (mm) * Height (mm)	2572 * 1126 * 1571
Dry weight (kg)	1405
Tank capacity (L)	190
Acoustic pressure level @1m in dB(A) 50Hz (75% PRP)	79
Sound power level guaranteed (Lwa) 50Hz (75% PRP)	96
Acoustic pressure level @7m in dB(A) 50Hz (75% PRP)	67



Dimensions DW compact version

Length (mm) * Width (mm) * Height (mm)	2600 * 1150 * 1583
Dry weight (kg)	1360
Tank capacity (L)	500

M138 - Dimensions DW soundproofed version

Length (mm) * Width (mm) * Height (mm)	2600 * 1150 * 1792
Dry weight (kg)	1705
Tank capacity (L)	500
Acoustic pressure level @1m in dB(A) 50Hz (75% PRP)	79
Sound power level guaranteed (Lwa) 50Hz (75% PRP)	96
Acoustic pressure level @7m in dB(A) 50Hz (75% PRP)	67

M138 - Dimensions DW 48h soundproofed version

Length (mm) * Width (mm) * Height (mm)	2600 * 1150 * 1858
Dry weight (kg)	1740
Tank capacity (L)	825
Acoustic pressure level @1m in dB(A) 50Hz (75% PRP)	79
Sound power level guaranteed (Lwa) 50Hz (75% PRP)	96
Acoustic pressure level @7m in dB(A) 50Hz (75% PRP)	67
* dimensions and weight without options	





Reference Conditions: 25°C Air Inlet Temperature, 40°C Fuel Inlet Temperature, 100 kPa Barometric Pressure; 10.7 g/kg of dry air Humidity. Intake Restriction set to maximum allowable limit; Fuel density at 0.85 kg/L. Data was taken from a single engine test according to the test methods, fuel specification and reference conditions stated above and is subjected to instrumentation and engine-to-engine variability. Test conducted with alternate test methods, instrumentation, fuel or reference conditions can yield different results. Data and specifications subject to change without notice.



Basic terminal block



M80



APM303



It is used as a basic terminal block for connecting a control unit. Offers the following functions:

- emergency stop button
- customer connection terminal block
- CE certified

The M80 is a dual-function control panel. It can be used as a basic terminal block for connecting a control unit and as an instrument panel with a direct read facility, with displays giving a global view of your generating set's basic parameters. Offers the following functions:

- Engine parameters: tachometer, working hours counter, coolant temperature indicator, oil pressure indicator
- emergency stop button
- customer connection terminal block
- CE certified

The APM303 is a versatile unit which can be operated in manual or automatic mode. It offers the following features:

- Measurements: phase-to-neutral and phase-to-phase voltages, fuel level (In option : active power currents, effective power, power factors, Kw/h energy meter, oil pressure and coolant temperature levels)
- Supervision: Modbus RTU communication on RS485
- Reports: (In option : 2 configurable reports)
- Safety features: Overspeed, oil pressure, coolant temperatures, minimum and maximum voltage, minimum and maximum frequency (Maximum active power P<66kVA)
 - Traceability: Stack of 12 stored events

For further information, please refer to the data sheet for the APM303

APM403



different results. Data and specifications subject to change without notice.

BASIC GENERATING SET AND POWER PLANT CONTROL

The APM403 is a versatile control unit which allows operation in manual or automatic mode

- Measurements : voltage and current
- kW/kWh/kVA power meters
- Standard specifications: Voltmeter, Frequency meter.
- Optional : Battery ammeter.
- J1939 CAN ECU engine control
- Alarms and faults: Oil pressure, Coolant temperature, Overspeed, Startup failure, alternator min/max, Emergency stop button.
- Engine parameters: Fuel level, hour counter, battery voltage.
- Optional (standard at 24V): Oil pressure, water temperature.
- Event log/ Management of the last 300 genset events.
- Mains and genset protection
- Clock management
- USB connections, USB Host and PC,
- Communications : RS485 INTERFACE
- ModBUS protocol /SNMP
- Optional : Ethernet, GPRS, remote control, 3G, 4G,
- Websupervisor, SMS, E-mails



STANDARD SCOPE OF SUPPLY

All our gensets are fitted with:

- Industrial water cooled DIESEL engine
- Electric starter & charge alternator
- Standard air filter
- Schneider or ABB electric circuit breaker, adapted to the short-circuit current of the generating set
- Single bearing alternator IP 23 T° rise/ insulation to class H/H
- Welded steel base frame with 85% vibration attenuation mounts
- 4 lifting points on the chassis, lifting bar on the top included from 165 kVA ESP or optional
- highly durable QUALICOAT certified epoxy paint
- frame height optimized to allow it to be moved safely by forklift
- enclosure made of new high-quality European steel with enhanced corrosion resistance
- IP 64 locks, made from stainless materials
- enclosures and base frames tested and analyzed by the French Corrosion Institut
- 100% of tanks tested for permeability
- Personal protection ensured by protective grilles on hot and rotating parts
- Separate 9 dB(A) silencer
- Fuel tank welded inside the genset frame
- Retention bund included for gensets up to 110 kVA ESP
- Charged DC starting battery with electrolyte
- Emergency stop button on the outside
- Flexible fuel lines & lub oil drain cock
- Exhaust outlet with flexible and flanges
- User's manual (1 copy)
- Packing under plastic film
- Delivered with oil and antifreeze liquid

CODES AND STANDARDS

Engine-generators set is designed and manufactured in facilities certified to standards ISO9001:2015 & ISO14001:2015. The generator sets and its components are prototype-tested, factory built and production tested and are in compliance with the relevant standards:

- Machinery Directive 2006/42/EC of May 17th 2006
- EMC Directive2014/30/UE
- Safety objectives set out in the Low Voltage Directive 2014/35/UE
- EN ISO 8528-13, EN 60034-1, EN 61000-6-1, EN 61000-6-2, EN 61000-6-3, EN 55011, EN 1679-1 et EN 60204-1

POWER RATINGS DEFINITION according to ISO8528-1 (2018-02 edition) and ISO-3046-1

Emergency Standby Power (ESP): The standby rating is applicable to varying loads for the duration of a power outage. There is no overload

capability for this rating. Average load factor per 24 hours of operation is <70%.

Prime Power (PRP): At varying load, the number of generator set operating hours is unlimited. A 10% overload capacity is available for one hour within 12 hour of operation. Average load factor per 24 hours of operation is <70%.



TERMS OF USE

According to the standard, the nominal power assigned by the genset is given for 25°C Air Intlet Temperature, of a barometric pressure of 100 kPA (100 m A.S.L), and 30% relative humidity. For particular conditions in your installation, refer to the derating table.

Reference Conditions: 25°C Air Inlet Temperature, 40°C Fuel Inlet Temperature, 100 kPa Barometric Pressure; 10.7 g/kg of dry air Humidity. Intake Restriction set to maximum allowable limit; Fuel density at 0.85 kg/L. Data was taken from a single engine test according to the test methods, fuel specification and reference conditions stated above and is subjected to instrumentation and engine-to-engine variability. Test conducted with alternate test methods, instrumentation, fuel or reference conditions can yield different results. Data and specifications subject to change without notice.